## Troubleshooting the problem of "the password doesn't match the key"

Several reasons cause the problem of "password does not match the key". When you launch our program, it pop up a windows says that "the password doesn't match the key". It would be rather annoyed news. So take the following steps to solve the problem.



First of all, insert the key to check if the light is on. If not, jump to step 3 directly; then, do from step 1.

1). Make sure that you have inserted the dongle (hardware key) and the user number in the **install manager** (open it from "star>all programs>SAi production suit>install manager) is the same as the one on the dongle (you can find an **USER ID** in the one side of the key). So you need plug in the responding key.

ser Number	Password		
18760	HXPY-MKG4-EJ	HN-HWCJ-3LHX-UKPU-MTNH-U	WYH
	Optional Passwo	ord	
ot For Resale. This is	an		6
raidadan cop ji			
			0

2). Even if you have checked every points of step 1 in detail, it still reminds you a wrong password. An utility "Getkey ID" can help to detect the true ID of the dongle. Open it from "\Util\GetKeyID" in the origin folder or CD. We will change another password or key to you if this happen.

GetKeyID	×
Key ID= 618760, Typ	pe=Sentinel
	确定

3). If the light doesn't on. Probably the driver isn't installed well. To install the driver,

insert the CD or open the installer folder, double click the "**Autorun**" then do next step and check the **Safenet** driver in the step as indicated below.

	I		
SAi Production Suite			5
Select Features Select the features setup will install.	St Prog	uction <sup>EXI<b>2Suite</b></sup>	
Select the features you want to inst	all, and deselect the feature	es you do not want to install.	
SAi Production Suite		463816 K	
✓ Samples ICC Profiles (size will vary)		26451 K O K	
SafeNet Sentinel System Driver	7.5.0.0	67 K	
Destination Folder			
C:\Program Files (x86)\SAi\SAi Pi	roduction Suite	Browse	
Space Required on C:	490334 K	Dish Course	
Space Available on C: InstallShield	21529492 K	Disk Space	
	< Back	Next > Cancel	

4). Still can't work? Then you may update the key driver. Download the latest driver from *http://www.safenet-inc.com/support-downloads/downloads-developer-kits/*.

5). Ensure that your firewall or anti-spy software do not block or clean our program or process. Please use the "ignore" or "trust" options when these soft wares conflict with our program.

6). If the light still off and can not found in **Window device manager** (right click "my computer" open manager, find "**Window device manager**", check if can find "SafeNet Sentinel Dual Hardware Key" ), try to insert it into other USB port of your computer or install it on other computer. The dongle may damaged if light off in the test said above. Mail us the dongle to detecting.



7). If you installed other programs that use a Safenet hardware key to activation also

may cause conflict. Try to avoid such a situation.

8). we strongly recommend you install a complete version of operation system to your computer, since our products need some OS service component. Make sure "SAiadmin" "SAidowmloader" "SAiLicSvr" is running in the service list. (process may differ under OS. The screen shot was in Windows 7. open Windows tasks manager by right click the task bar.)

用程序 进程 服务 性能 联网	用户							
映像名称	用户名	CPV 内存	(专用	I/O 读取字节	I/O 写入字节	I/0 其他字节	描述	
notepad.exe opera.exe *32 PsiService_2.exe *32	Administrator Administrator SYSTEM	00 00 10 00	1,716 K DO,024 K 996 K	65, 004 84, 116, 389	24, 228, 824	28, 066 535, 074, 205 17, 852	记事本 Opera Internet Brows PsiService PsiServic	ser ce
raysat_3dsmax2011_32server. exe *32 SA1Admin. exe *32	SYSTEM	00	1,112 K 1,232 K	17, 588 29, 272		21, 872 22, 484	raysat_3dsmax2011_32 TODO: <file descript<="" td=""><td>2server tion≻</td></file>	2server tion≻
SAiDownloaderVista.exe *32 SAiDownloaderVistaUI.exe *32	SYSTEM	00	1,712 K 1,600 K	5, 078, 766 5, 047, 246		3, 509, 860 3, 505, 810	TODO: (File descrip) TODO: (File descrip)	tion> tion>
SAiLicSvr. exe *32 SearchFilterHost. exe	SYSTEM	00	1,524 K 1,852 K	281, 376 19, 752		367, 854 25, 418	License Server Microsoft Windows Se	earch Filter Host
Windows 任务管理器 サイト 法市(の) 赤売の 熟計(山)								
Windows 任务管理器 キ(F) 违项(O) 查置(V) 帮助(H) 田祝友 単純 昭泰 一 単純 単純								
Windows 任务管理器 (F) 选项(O) 查看(V) 帮助(H) 用程序 进程 服务 性能 联	网用户							
Windows 任务管理器 集(F) 选项(O) 查看(V) 帮助(H) 用程序 进程 服务 性能 联 名称	网 用户 PID 描述				状态	工作组		
Windows 任务管理器 年(F) 选项(C) 查看(V) 帮助(H) 用程序 进程 服务 性能 联 名称 ApcSs (SAiAdmin SAiDownLoader SAiDownLoader SAiDownLoader	网 用户 FID 描述 768 Remote Proced 2932 SAiAdmin 708 SAiDownLoader 2512 SAiDownLoader	ure Call (RPC Vista	:)		状态 正在运行 正在运行 正在运行 正在运行	工作组 cpcss 智慧缺 智敏		

9). cached Temp files in the RAM can cause error. Try to restart or log off if the dongle does not work after the using of other version of our program.

10). Use the LAN connected printer while another computer in the network has problem with the dongle. This situation is also need to pay attention.